



Female XLR cable type connector 110 Ω input - female BNC 75 Ω output.  
 For matching balanced 110 ohm digital audio circuits to unbalanced 75 ohm video circuits.

**Features & Benefits**

- Allow long cable runs for digital audio signals via low attenuation coax lines
- Match balanced to coaxial lines
- Match impedances 110 Ω to 75 Ω
- Simple to use, passive units

**Technical Information**

Product	NADITBNC-FX
Connection Type	Adapter Female Cable type XLR to Female BNC
Frequency range	0.1 - 6 MHz
Rated voltage	≤ 5 V p-p
VSWR	< 1.1
Return loss	> 26.4 dB
Insertion Loss	< 0.3 dB @ 0.1 MHz to 10 MHz

**Drawing**

