



**Configuration:**

LA-344 Replacement Mounting Hardware (For LT-84, LA-141 only)

**Product Overview:**

Easily mount and adjust your LT-84 ListenIR Transmitter/Radiator Combo and LA-141 ListenIR Expansion Radiator for any space or any installation with the LA-344 Replacement Mounting Hardware kit. The modular system allows the unit to be tilted 190° and rotated up to 360° with a locking ring to hold the desired position, and the included set screw adjusting options for a tamper-resistance setup. The length can also be adjusted to 2 in. (5.08 cm), 4 in. (10.16 cm), or 6 in. (15.24 cm) depending on the needs of your setup.

**Highlights:**

- Flexible, versatile mounting system for wall, ceiling, or table use
- 190° tilt adjustment and up to 360° rotation for any setup or installation
- 5.08 cm (2 in.), 10.16 cm (4 in.), or 15.24 cm (6 in.) length adjustment options

- Includes:** One (1) Wall Base  
 One (1) Ceiling T-Bar Base  
 One (1) Black Vinyl Base Cover  
 Two (2) Shafts  
 One (1) Adjustable Head with Locking Ring  
 One (1) Alan Head Tamper Resistant Set Screw  
 One (1) Alan Wrench  
 One (1) 1/4 x 20 all-thread

Product Specification: Replacement Mounting Hardware (For LT-84, LA-141 only)	
Physical	
Shipping Weight	1.0 lbs (0.5 kg)
Base 2	T-Bar Clip for drop ceiling rails, 1/4-20 stud
Base 1	2" (50.8 mm) round base with four 0.188" (4.8mm) holes on 1.6" (40.6mm) bolt circle for solid surface mounting, 1/4-20 stud
Base Cover	Matching black vinyl cover adds a finished look to either base
Shafts	Two aluminum shafts, 0.5" (12.7mm) diameter, 2" (50.8mm) long, black, 1/4-20 stud
Adjustable Head	Fully adjustable with locking ring, 190° Tilt, 360° Turn and 360° Rotation)
Finished Lengths	2" (50.8mm), 4" (101.6mm) or 6" (152.4mm) long mount
Unit Weight	0.3 lbs (166.5g)
Maximum Load Weight	3 lbs (1.36 kg)